http://dustbunny.physics.indiana.edu/~paul/hallDrd

GlueX (Jefferson Lab Hall D) Electronics R&D

Indiana University Light Quark Physics Group

Paul Smith Indiana University, Department of Physics, Bloomington, IN, 47405

For the Jefferson lab GlueX experiment, we will be developing pipelined Flash ADC front end electronics. Traditionally, particle physics experiments delay detector signals in long coaxial cables to allow time for a trigger to be formed:





The pipeline approach continuously digitizes the detector data and stores the digital information. In parallel, the trigger uses the digital information to find interesting events. When the trigger condition is satisfied, time-delayed information is extracted from the pipeline for further processing by the data acquisition system.

The pipeline can be implemented with Dual Port Random Acess Memory:



The FADC data is continuously written into the Dual Port RAM. Upon receipt of a level 1 trigger, the data from the associated time slice is read from the other port. This scheme introduces no deadtime since new data continue to be written while the old data is read.

The FADC data is also used to form the level 1 trigger. A tree of adders sums information from the various channels in a detector system:



Within the next few years, this hardware will be prototyped at IU. Since the Hall D detector will require 10,000+ channels of this electronics, optimizing the cost is extremely important.

Flash ADCs are specified in terms of samples per second and number of bits of resolution. The individual samples can be added together to calculate the charge contained in a pulse:

Pulse Digitization



Our goal is to optimize the resolution at which the pulses are digitized by varying the sampling frequency and the sampling depth.

The sampling depth is related to the smallest voltage change to which the device is sensitive. A depth of n bits will provide 2^n divisions on the voltage scale

The sampling frequency is the rate at which the pulse is sampled. For shorter pulses higher frequencies are necessary.

We varied the sampling rate and bit depth for simulated pulses from a slow photomultiplier (FEU84) and a fast photomultiplier (XP2020). The variance in the charge measurement divided by the measured charge is plotted:

FEU 84-3


σ/q
10^{-1}
10^{-2}
4
6
8
10
12
14
16
Sampling Depth (bits)
100
150
200
250
300
350
400
450
500
550
Sampling Frequency (MHz)


Sampling Depth (bits)
16
14
12
10
8
6
4
100
150
200
250
300
350
400
450
500
550
Sampling Frequency (MHz)
10^{-1}
10^{-2}



For the FEU84-3, summing the FADC samples results in an energy resolution better than the intrinsic

resolution of lead glass:



A Xilinx XC2S50 gate array which implements the dual port RAM buffering, feature extraction, and an interface to the PCI bus has been designed and simulated. Here is a block diagram:



Here is a "floorplan" of the gate array:



Here is the routing for the gate array:



Here are schematics of a PCI card to test the FADC and Xilinx gate array:


VP5
L2
L3
C1
0.01 uF
C2
10 uF
C47
100 uF
U2
fadc
SPT77
VP5
R18
R24
U3
diffamp
VP5
R21
U3
IN
R30
CW
10K
R26
OUT
R15
CR1
VOCM
OUT_N
R16
C56
0.01 uF
R27
IN_N
AD8132
VIN
VCM
VIN_N
R20
R19
CLK
CLK_N
RESET_
RESET
VP5
PD
DMODE2
DMODE1
J2
CR2
R17
R34
U2
C4
0.01 uF
C3
10 uF
C48
100 uF
VP5VP3p3
VM5
VM5
R13
CLK250VDD
R22
VP5
clkosc250
R28
VDD
CLK_Nf
CLK_Ne
CLK
GND
C39
0.1 uF
U4
C37
4.7 uF
R14
R23
R29


U1
fpga
XC2S50
VP3p3
J8
J7
J6
J5
C15
0.1 uF
U8
XC17S50A
prom
CLK
DATA
RESET_N
OE_N
M2
M1
M0
TCK
TDI
TDO
TMS
CCLK
DIN
INIT_N
DONE
PROGRAM_N
TRIG_IN
TRIG_OUT
TRIG_FIFO_FULL
OUT_FIFO_FULL
DLLPLOCK
DLLDLOCK
PROC_CLK
DCLK
FADC_DAT(15)
FADC_DAT(14)
FADC_DAT(13)
FADC_DAT(12)
FADC_DAT(11)
FADC_DAT(10)
FADC_DAT(9)
FADC_DAT(8)
FADC_DAT(7)
FADC_DAT(6)
FADC_DAT(5)
FADC_DAT(4)
FADC_DAT(3)
FADC_DAT(2)
FADC_DAT(1)
FADC_DAT(0)
QL1
VP5
C16
0.1 uF
clkosc U5
CLK
VP2p5
6 x 0.01uF
4 x 4.7uF
C17 C18 C19 C20 C21 C22 C11 C12 C13 C14
8 x 0.01uF
4 x 100uF
C29 C30 C31 C32 C25 C26 C27 C28 C6 C7 C8 C9


VP5
U6
75107
1EN
J3
R32
CR3
C54
0.1 uF
C53
0.1 uF
C52
0.1 uF
R31
VM5
VP5
VM5
U7
EN1
75112
EN2
TRIG_OUT
R33
VP5
C51
0.1 uF
C50
0.1 uF
VM5



Here is the printed circuit:


DATEL
DC/DC CONVERTER
ANA IN
AGND
R24
R21
K44
R20
R18
R19
R27
R16
R15
K45
R17
R29,28
R14,13
R23,22
GND
3.3
TMS
TCK
TDI
TDO
CCLK
DIN
OSC
VDD
SP1
SP2
SP3
SP6
SP5
SP4
M0
M1
M2
XILINX
SPARTAN
R33
U7
TRIG
OUT
IN
K46
U6
R32
R31
INIT
DONE
PROGRAM
GND
GND
GND



Higher resolution and printable versions of the figures are available here.
Sample waveforms are available here.
Register assignments and programming information is available here.
Linux driver software is available here.
More information about the GlueX experiment is available here.